

# Microwave

Accessories for Microwave Scalar and System Analyzers

Data Sheet

**COBHAM**

The most important thing we build is trust



The following optional accessories are designed for use with the 6200B Series of Microwave Test Sets, the 6820 Series Scalar Analyzers and the 6840 Series Microwave System Analyzers.

The 6230A Series of scalar detectors provides excellent linearity and flatness from a built-in EEPROM that allows near power meter performance. Diode linearity correction provides improved performance over a wide dynamic range.

The 6240 Series of fault locators provides measurement of both return loss (VSWR) and fault location (distance to fault) from a single measuring port.

Ratio measurements require a power splitter to be used and a range is available for frequencies up to 40 GHz.

Power dividers can be used for simple power division or can be operated with a scalar detector and the 6800 Series to generate a low cost fault location system.

The recently launched Option 25A/B provides internal pulse modulator capability on the majority of the 6810 Series and 6820 Series products. (Refer to 6810/6820 product data sheets for details)

External pulse modulators 6146/6147 are also available and provide external pulse modulation capability for all of the 6200B Series, 6810 series, 6820 Series and 6840 Series.

The 6146 is a high performance active pulse modulator providing fast rise and fall times with 70 dB on/off ratio over a frequency range of 500 MHz to 18 GHz. The 6147 operates from 70 MHz to 40 GHz but is a passive pulse modulator with lower on/off ratio and slower rise/fall time performance.

## 6230A/L Series Scalar Detectors

The 6230A and 6230L Series of scalar detectors have EEPROM correction for improved frequency response. Users can achieve swept power measurements with accuracy close to that achieved with a power sensor.

The 6230A Series scalar detectors have typically 85 dB dynamic range (-65 dBm to +20 dBm) and are used when best sensitivity and maximum dynamic range are required. The 6230L Series scalar detectors (-59 dBm to +26 dBm typically) have integral input attenuators. This provides improved input match and greater power handling capability. The 6230L Series detectors should be used when measuring low loss devices, such as semi-rigid cables or when measuring high power devices such as amplifiers.



## Scalar Detectors (with EEPROM correction)

### Ordering

Number	Version
6230A Series	Standard Detectors (-65 dBm to +20 dBm) typical
6230A	10 MHz to 20 GHz, N type (m)
6232A	1 MHz to 3 GHz, N Type (m)
6233A	10 MHz to 26.5 GHz, 3.5 mm (m)
6234A	10 MHz to 46 GHz, 2.92 mm (m)
6230L Series	Low VSWR Detectors (-59 dBm to +26 dBm) typical
6230L	10 MHz to 20 GHz, N type (m)
6233L	10 MHz to 26.5 GHz, 3.5 mm (m)
6234L	10 MHz to 46 GHz, 2.92 mm (m)

### Supplied Accessories

43139/099 1.5 m DC Cable

### Optional Accessories

43139/100 3 m DC Cable  
 43139/101 10 m DC Cable  
 43139/102 25 m DC Cable  
 43139/103 50 m DC Cable

Typical specifications are non-warranted.

## SPECIFICATION

	6230A	6230L	6232A	6233A	6233L	6234A	6234L
Frequency Range	10 MHz to 20 GHz	10 MHz to 20 GHz	1 MHz to 3 GHz	10 MHz to 26.5 GHz	10 MHz to 26.5 GHz	10 MHz to 46 GHz	10 MHz to 46 GHz
Dynamic range							
AC detection:	-65 dBm to +20 dBm, typical	-59 dBm to +26 dBm, typical	-65 dBm to +20 dBm, typical	-65 dBm to +20 dBm, typical	-59 dBm to +26 dBm, typical	-65 dBm to +20 dBm, typical	-59 dBm to +26 dBm, typical
DC detection:	-60 dBm to +20 dBm, guaranteed	-54 dBm to 26 dBm, guaranteed	-60 dBm to +20 dBm, guaranteed	-60 dBm to +20 dBm, guaranteed	-54 dBm to +26 dBm, guaranteed	-60 dBm to +20 dBm, guaranteed	-54 dBm to +26 dBm, guaranteed
Maximum RF input VSWR							
1 to 10 MHz	-----	-----	1.43	-----	-----	-----	-----
10 to 40 MHz	1.4	1.4 1.14	1.4	1.4	1.58	1.5	-----
40 to 100 MHz	1.15	1.1 1.14	1.15	1.1 1.15	1.15	-----	-----
0.1 to 2 GHz	1.12	1.1 1.14 (to 2.7 GHz)	1.12	1.1 1.12	1.1	-----	-----
2 to 5 GHz	1.17	1.1 1.2 (to 3 GHz)	1.17	1.1 1.33	1.1	-----	-----
5 to 18 GHz	1.29	1.15-----	1.29	1.15 1.33	1.15	-----	-----
18 to 20GHz	1.5†	1.22†	-----	1.5	1.22	1.5	1.22
20 to 26.5 GHz	-----	-----	-----	1.5	1.22	1.5	1.22
26.5 to 33 GHz	-----	-----	-----	-----	-----	1.5	1.31
33 to 40 GHz	-----	-----	-----	-----	-----	1.95	1.31
Linearity	0.2 dB/10 dB but not >0.5 dB in total	0.2 dB/10 dB but not >0.5 dB in total	0.2 dB/10 dB but not >0.5 dB in total	0.2 dB/10 dB but not >0.5 dB in total	0.2 dB/10 dB but not >0.5 dB in total	0.2 dB/10 dB but not >0.5 dB in total	0.2 dB/10 dB but not >0.5 dB in total
Frequency Response (EEPROM corrected)	±0.2 dB	±0.2 dB	±0.2 dB	±0.2 dB	±0.2 dB	±0.2 dB (±0.4 dB >26.5 GHz)	±0.2 dB (±0.4 dB >26.5 GHz)
Connector Type N (m)	Precision Type N (m)	Precision Type N (m)		Precision 3.5 mm (m)	Precision 3.5 mm (m)	Precision 2.92 mm (m)	Precision 2.92 mm (m)
Length	89 mm	89 mm	73 mm	80 mm	80 mm	88.5 mm	88.5 mm
Width	33.5 mm	33.5 mm	33.5 mm	33.5 mm	33.5 mm	33.5 mm	33.5 mm
Weight	151 g	151 g	180 g	151 g	151 g	149 g	149 g

† Specifications involving Type N connectors above 18 GHz are not traceable to national standards as these do not exist at present.

†† Specifications involving 2.92 mm connectors above 40 GHz are not traceable to national standards as these do not exist at present.

## Return Loss Bridge

For measurement of return loss (or VSWR) with a scalar analyzer an autotester is the best solution. An autotester is an RF bridge with a built in detector. An autotester is an RF bridge with a built in detector. An RF bridge needs to be used with a 6230 Series detector for the measurement of return loss. An autotester with the correct type and sex of test port connector should be used because test port adapters seriously degrade directivity and hence measurement accuracy.



## Ordering Number

## Version

59999/170 Return Loss Bridge 5 MHz to 2 GHz N (f)

\*Not supplied with open/short circuit or adapter cable

## Supplied With

Open/Short Circuit

43137/604 Autotester adapter cable

## Optional Accessories

43139/107 1.5 m Autotester adapter cable

## SPECIFICATION

Model/Test Port Connector Characteristic	59999/151 GPC-7 (Discontinued)	59999/158 N (m) 59999-159 N (f) (Discontinued)	59999/152 WSMA (m) 59999/166 WSMA (f) (Discontinued)	59999/168 2.92 mm (m) 59999/169 2.92 mm (f) (Discontinued)	59999/170
Frequency range	10 MHz to 18 GHz	10 MHz to 18 GHz	10 MHz to 26.5 GHz	10 MHz to 40 GHz	5 MHz to 3 GHz
Directivity					
0.01 to 18 GHz	40 dB	38 dB	40 dB	35 dB	5 MHz to 50 MHz >25 dB
18 to 26.5 GHz	N/A	N/A	38 dB	32 dB	50 MHz to 3 GHz >40 dB
26.5 to 40 GHz	N/A	N/A	N/A	30 dB	
Frequency sensitivity	±1.2 dB	±1.5 dB	±2.0 dB	±3.0 dB	
Accuracy <sup>1</sup>					
0.01 to 8 GHz	0.010 +0.06r <sup>2</sup>	0.013 +0.08r <sup>2</sup>	0.010 +0.10r <sup>2</sup>	0.018 +0.15r <sup>2</sup>	
8 to 18 GHz	0.010 +0.10r <sup>2</sup>	0.013 +0.12r <sup>2</sup>	0.010 +0.10r <sup>2</sup>	0.018 +0.15r <sup>2</sup>	
18 to 26.5 GHz	N/A	N/A	0.013 +0.12r <sup>2</sup>	0.025 +0.15r <sup>2</sup>	
26.5 to 40 GHz	N/A	N/A	N/A	0.032 +0.18r <sup>2</sup>	
Insertion loss <sup>2</sup>	6.5 dB Nominal	6.5 dB Nominal	6.5 dB Nominal	6.5 dB Nominal	<7.5 dB Nominal
Maximum input power	+27 dBm	+27 dBm	+27 dBm	+27 dBm	+31 dBm
Input connector	N (f)	N (f)	2.92 mm (f)	2.92 mm (f)	N (f)
Size <sup>3</sup>	76 x 50 x 28 mm	76 x 50 x 28 mm	54 x 38 x 19 mm	54 x 38 x 19 mm	115 x 51 x 29 mm
Weight	340 g	340 g	198 g	198 g	680 g

<sup>1</sup>Where r = measured reflection coefficient - includes directivity and test port reflection effects over the specified frequency range.

<sup>2</sup> Nominal value from input port to test port

<sup>3</sup> Excluding connectors and cable

## Power Splitters/Dividers

Three different power splitters are available with N type, 3.5 mm or 2.92 mm connectors. Power splitters are primarily intended to be used in scalar measuring systems, in a ratioing arrangement, where a reference channel is used to improve source match. Power dividers can be used as a simple accessory for single Autotesters and Bridges input fault location measurements. This technique offers less accuracy than a Test Head or Fault Locator but is an economical measurement technique.



## Power Splitters/Dividers

54311/123	Power Splitter DC to 18 GHz, Type N
54311/124	Power Splitter DC to 26.5 GHz, 3.5 mm
54311/161	Power Splitter DC to 40 GHz, 2.92 mm
54311/187	Power Divider DC to 18 GHz, Type N
54311/188	Power Divider DC to 26.5 GHz, 3.5 mm

## 6240 Series Fault Locators

The 6240 Series Fault Locators provide a quick and convenient method of measuring return loss, VSWR and fault location from a single test port. Fault locators are compact and rugged making them ideal for field measurements.

Typical applications include antenna and antenna feeder testing of mobile communications base stations and waveguide feeds on microwave towers.

When used with the 6820 scalar analyzer or 6840 Series microwave system analyzers the display can show simultaneously on two channels, return loss and fault location traces.

As both measurements are made from a single test port, setup time is reduced and a system can be completely characterized without the need to make repetitive reconnections.



## Fault Locators

### Ordering

Numbers	Versions
6242F	10 MHz to 3 GHz, N (f)
6242M	10 MHz to 3 GHz, N (m)
6240F	10 MHz to 20 GHz, N (f)
6240M	10 MHz to 20 GHz, N (m)
6243F	10 MHz to 26.5 GHz, 3.5 mm (f)
6243M	10 MHz to 26.5 GHz, 3.5 mm (m)
6241	10 MHz to 20 GHz, 7 mm

### Supplied Accessories

43138/663	1.5 m DC Cable (2 off) Open/Short Circuit (Not 6242) 50 W Termination
-----------	---

### Optional Accessories

43138/664	3.0 m DC Cable (2 off necessary, for use with 3.0 m RF or microwave cable)
-----------	--

### RF Ruggedized Cables for Fault Locators

54311/199	1.5 m, 3 GHz, N (m) to Right Angle N (m)
54311/200	3.0 m, 3 GHz, N (m) to Right Angle N (m)

### Microwave Ruggedized Cables for Fault Locators

54311/197	1.5 m, 20 GHz, N (m) to Right Angle N (m)
54311/198	3.0 m, 20 GHz, N (m) to Right Angle N (m)
54311/201	1.5 m, 26.5 GHz, 3.5 mm (m) to Right Angle 3.5 mm (m)
54311/202	3.0 m, 26.5 GHz, 3.5 mm (m) to Right Angle 3.5 mm (m)

## SPECIFICATION

	6242F (Female Test Port) 6242M (Male Test Port)	6240F (Female Test Port) 6240M (Male Test Port)	6241 (7 mm Test Port)	6243F (Female Test Port) 6243M (Male Test Port)
Frequency Range				
Fault Location	10 MHz to 3 GHz	10 MHz to 20 GHz	10 MHz to 20 GHz	10 MHz to 26.5 GHz (usable to 40 GHz)
Return Loss	10 MHz to 3 GHz	10 MHz to 18 GHz	10 MHz to 18 GHz	10 MHz to 26.5 GHz
Test Port Connector	Type N	Type N	7 mm	3.5 mm
Input Connector	Type N female	Type N female	Type N female	3.5 mm female
Test Port Return Loss				
10 MHz to 3 GHz	20 dB	20 dB	20 dB	20 dB
3 GHz to 18 GHz	—	20 dB	20 dB	20 dB
18 GHz to 26.5 GHz	—	—	—	15 dB
Directivity				
10 MHz to 50 MHz	35 dB	35 dB	35 dB	35 dB
50 MHz to 3 GHz	38 dB	38 dB	38 dB	38 dB
3 GHz to 8 GHz	—	35 dB	35 dB	35 dB
8 GHz to 18 GHz	—	34 dB	35 dB	32 dB
18 GHz to 26.5 GHz	—	—	—	32 dB
Accuracy of return loss <sup>1</sup>				
10 MHz to 50 MHz	0.018 + 0.1 r <sup>2</sup>	0.018 + 0.1 r <sup>2</sup>	0.018 + 0.1 r <sup>2</sup>	0.018 + 0.1 r <sup>2</sup>
50 MHz to 3 GHz	0.013 + 0.1 r <sup>2</sup>	0.013 + 0.1 r <sup>2</sup>	0.013 + 0.1 r <sup>2</sup>	0.013 + 0.1 r <sup>2</sup>
3 GHz to 8 GHz	—	0.018 + 0.1 r <sup>2</sup>	0.018 + 0.1 r <sup>2</sup>	0.018 + 0.1 r <sup>2</sup>
8 GHz to 18 GHz	—	0.018 + 0.1 r <sup>2</sup>	0.018 + 0.1 r <sup>2</sup>	0.025 + 0.1 r <sup>2</sup>
18 GHz to 26.5 GHz	—	—	—	0.025 + 0.18 r <sup>2</sup>
Insertion Loss	7 dB Nominal	7 dB Nominal	7 dB Nominal	7 dB Nominal
Max input power	+26 dBm	+26 dBm	+26 dBm	+26 dBm
Size	79 x 73 x 34 mm	79 x 73 x 34 mm	79 x 73 x 34 mm	79 x 73 x 34 mm
Weight	358 g	358 g	362 g	315 g

<sup>1</sup> Where r = measured reflection coefficient - includes directivity and test port reflection effects over the specified frequency range.

## 6146 and 6147 Pulse Modulators

The 6146 Pulse Modulator is ideal for modulating RF and Microwave signals to enable testing of radar systems. Its wide frequency range of 70 MHz to 20 GHz means it can test both the RF and IF performance of the radar.

Fast rise and fall times coupled with >70 dB ON/OFF ratio ensures that the 6146 can be used to test the majority of modern radars. Modulation is controlled by a TTL input. Any suitable pulse generator can be used to drive the 6146. An integral amplifier gives the 6146 an insertion gain of 5 dB. This enhances the ability to measure the dynamic range of a radar compared with traditional pulse modulators that typically have an insertion loss up to 10 dB.

The 6146 is a small lightweight and rugged package. It can be connected directly onto the output of a signal source and has type N connectors. When used with the 6840 series Microwave System Analyzer it is powered with the accessory power supply.

The combination of a 6146 and a 6840 fitted with an internal attenuator forms the basis of an excellent solution for testing radar systems. The fundamental radar tests of minimum discernible signal, 1 dB compression and subclutter rejection are made simple.

An internal pulse modulator Option 25A/B is now available for most 6810 and 6820 Series products. (Refer to 6810/6820 product data sheets for details)



## SPECIFICATIONS

### 6146

#### Frequency Range

500 MHz to 18 GHz

useable from 70 MHz to 20 GHz

#### ON/OFF Ratio

>70 dB from 500 MHz to 18 GHz

>35 dB 70 MHz to 200 MHz

>60 dB 200 MHz to 500 MHz

#### Rise/Fall Time

<5 ns

#### Delay Time

≤20 ns

#### Minimum Pulse Width

50 ns

#### Maximum PRF

20 MHz

#### Pulse Width Compression

≤10 ns

#### Video Breakthrough

<150 mV pk-pk 500 MHz to 18 GHz

<200 mV pk-pk 70 MHz to 500 MHz

#### Switch Generated RF

<-35 dBm from 70 MHz to 500 MHz

<-50 dBm from 500 MHz to 1 GHz

<-70 dBm from 1 GHz to 18 GHz

#### Reverse Power Damage Level

+20 dBm, ±42 V DC

#### Harmonics

≤-15 dBc for >10 dBm output power

#### Power Accuracy

±1 dB after user calibration

#### Insertion Gain at +23°C

>5 dB 500 MHz to 18 GHz

Gain temperature coefficient, -0.05/°C typical

#### Minimum Output Power at +23°C

(with +5 dBm input power)

≥+8 dBm 500 MHz to 18 GHz

#### Input Damage Level

+20 dBm, ±42 V DC

#### Modulation Input Type

Standard TTL levels. BNC input for RF ON when logic level low

#### Modulation Input Impedance

>10 kΩ

## RF Input

Connector

Type N (m) 50  $\Omega$

Return loss

>5 dB 70 MHz to 200 MHz Typical

>8 dB 200 MHz to 18 GHz Typical

## RF Output

Connector

Type N (f) 50  $\Omega$

Return loss

>10 dB 200 MHz to 6 GHz Typical

>6 dB 6 GHz to 18 GHz Typical

## Electromagnetic Compatibility

Conforms with the protection requirements of the EEC Council Directive 89/336/EEC

Complies with the limits specified in the following standards:

EN55011 Class B CISPR 11

EN50082-1 IEC 801-2,3,4

## Safety

Complies to IEC 348

## Rated Range of Use

### Temperature

0 to +50°C

### Humidity

Up to 93 % humidity at 40°C

## Conditions of Storage and transport

### Temperature

-40 to +70°C

### Humidity

Up to 93 % humidity at 40°C

### Altitude

Up to 4,600 meters (15,000 feet)

## Dimensions and Weight

148 mm x 86 mm x 41 mm

400 g

## Supply Voltages

+18 to 36 V DC, 500 mA

Available from the optional AC adapter.

## 6147

---

## Frequency Range

70 MHz to 40 GHz

## ON/OFF Ratio

>23 dB

## Rise/Fall Time

<150 ns

## Pulse Width Compression

<150 ns

## Minimum Pulse Width

500 ns

## Maximum PRF

1 MHz

## Insertion Loss

<10 dB

## Minimum Output Power

(with +5 dBm input power)  $\geq$  -5 dBm

## Reverse Power Damage Level

+20 dBm,  $\pm$ 42 VDC

## Input Damage Level

+20 dBm,  $\pm$ 42 VDC

## Modulation Input Type

Standard TTL, BNC input for RF ON when logic level low

## Modulation Input Impedance

>10 k $\Omega$

## Input/Output Return Loss

7 dB typ

## RF Input/Output Connectors

2.92 mm (f)

## Electromagnetic Compatibility

Conforms with the protection requirements of the EEC Council Directive 89/336/EEC. Conforms with the limits specified in the following standards.

IEC/EN61326-1 Conducted emission Class A

Radiated emission Class B. Immunity Table 1 Performance Criterion B

## Safety

Conforms with the requirements of EEC Council Directive 73/23/EEC (as amended) and the product safety standard IEC / EN 61010-1 for class 1 (or 3) portable equipment, for use in a Pollution Degree 2 environment. The instrument is designed to be operated from an Installation Category 2 (or / and 1) supply.

## Operating Temperature

0°C to +50°C

## Dimensions and Weight

112 mm x 86 mm x 41 mm, 450g

## Supply Voltages

+12 V DC 400 mA & -12 V DC 70 mA

Available from the optional AC adapter

## ACCESSORIES – PART NUMBER LIST

When ordering please quote the full ordering number information.

### Ordering numbers

6146	500 MHz to 18 GHz Pulse Modulator
6147	70 MHz to 40 GHz Pulse Modulator
54441/019	AC Power Supply (for 6146 & 6147)

### 6230A/L SCALAR DETECTORS

6230A Series	Standard Detectors (-65 dBm to +20 dBm typical)
6230A	10 MHz to 20 GHz, N type (m)
6232A	1 MHz to 3 GHz, N Type (m)
6233A	10 MHz to 26.5 GHz, 3.5 mm (m)
6234A	10 MHz to 46 GHz, 2.92 mm (m)
6230L Series	Low VSWR detectors (-59 dBm to +26 dBm typical)
6230L	10 MHz to 20 GHz, N type (m)
6233L	10 MHz to 26.5 GHz, 3.5 mm (m)
6234L	10 MHz to 46 GHz, 2.92 mm (m)

### RF BRIDGE

59999/170	5 MHz to 3 GHz N (f)
-----------	----------------------

### FAULT LOCATORS

#### Fault Locators

6242F	10 MHz to 3 GHz, N (f)
6242M	10 MHz to 3 GHz, N (m)
6240F	10 MHz to 20 GHz, N (f)
6240M	10 MHz to 20 GHz, N (m)
6243F	10 MHz to 26.5 GHz, 3.5 mm (f)
6243M	10 MHz to 26.5 GHz, 3.5 mm (m)
6241	10 MHz to 20 GHz, 7 mm

#### Microwave Ruggedized Cables for Fault Locators

54311/197	1.5 m, 18 GHz, N (m) to Right Angle N (m)
54311/198	3.0 m, 18 GHz, N (m) to Right Angle N (m)
54311/201	1.5 m, 26.5 GHz, 3.5 mm (m) to Right Angle 3.5 mm (m)
54311/202	3.0 m, 26.5 GHz, 3.5 mm (m) to Right Angle 3.5 mm (m)

#### RF Ruggedized Cables for Fault Locators

54311/199	1.5 m, 3 GHz, N (m) to Right Angle N (m)
54311/200	3.0 m, 3 GHz, N (m) to Right Angle N (m)

### Microwave Ruggedized Cables

54311/116	1.5 m, 20 GHz, N (m) to N (m)
54311/109	3.0 m, 20 GHz, N (m) to N (m)
54311/117	1.5 m, 26.5 GHz, 3.5 mm (m) to 3.5 mm (m)
54311/110	3.0 m, 26.5 GHz, 3.5 mm (m) to 3.5 mm (m)

### Scalar Detector and Fault Locator DC Cables

Scalar Detector cables for use in conjunction with 6800 Series

(Color coded blue)

43139/099	1.5 m, DC Cable
43139/100	3.0 m, DC Cable
43139/101	10 m, DC Cable
43139/102	25 m, DC Cable
43139/103	50 m, DC Cable

### Scalar Detector cables for use with 6240 Series fault locator

43138/663	1.5 m
43138/664	3.0 m
43138/665	10 m
43138/666	25 m
43138/667	50 m
431389/007	100 m
43138/897	120 m
43138/837	150 m

### MILLIMETER WAVEGUIDE, SINGLE DIODE HARMONIC MIXERS

Model Number	Frequency Range	Waveguide Designation	Flange Type
M42HW	18-26.5 GHz	WR42, WG20, R220	UG-597/U
M28HW	26.5-40 GHz	WR28, WG22, R320	UG-599/U
M22HW	33-50 GHz	WR22, WG23, R400	UG-383/U
M19HW	40-60 GHz	WR19, WG24, R500	UG-383/U
M15HW	50-75 GHz	WR15, WG25, R620	UG-385/U
M12HW	60-90 GHz	WR12, WG26, R740	UG-387/U
M10HW	75-110 GHz	WR10, WG27, R900	UG-387/U

For other frequencies and sizes please consult factory for details.

A Diplexer (DPL313A) is required for use with the mixers listed above. It is supplied with two SMA (m) barrel adapters for IF and LO interconnection to the spectrum analyzer Option 020 connectors and a 1 meter long, high quality interconnecting cable for connection between mixer and diplexer.

## ACCESSORIES

	<b>Power Splitters/Dividers</b>	54311/133	
54311/123	Power Splitter DC to 18 GHz, Type N	54311/134	
54311/124	Power Splitter DC to 26.5 GHz, 3.5 mm	54311/135	
54311/161	Power Splitter DC to 40 GHz, 2.92 mm		
54311/187	Power Divider DC to 18 GHz	54311/170	
54311/188	Power Divider DC to 26.5 GHz	54311/112	
	<b>RF Ruggedized Cables for Bridges and Dividers</b>	43129/189	
54311/195	1.5 m, 3 GHz, N (m) to N (m)	43139/042	
54311/196	3.0 m, 3 GHz, N (m) to N (m)	46884/560	
	<b>Fixed Loads</b>	43137/604	
54421/020	7 mm Fixed Load	43139/107	
54421/021	3.5 mm (f) Fixed Load		
54421/022	3.5 mm (m) Fixed Load	54351/022	
54421/023	N (m) Fixed Load	54351/025	
54421/024	N (f) Fixed Load		
	<b>Precision Adapters</b>	54351/027	
54311/175	N (m) to N (m)		
54311/167	N (m) to N (f)	56534/901	
54311/174	N (f) to N (f)	56534/902	
54311/176	N (f) to 3.5 mm (f)	56534/903	
54311/177	N (m) to 3.5 mm (f)	56534/904	
54311/178	N (m) to 3.5 mm (m)		
54311/185	N (f) to 3.5 mm (m)	56534/904	
54311/137	N (m) to TNC (f)		
54311/138	N (m) to TNC (m)		
54311/139	N (f) to TNC (f)	59000/327	
54311/186	N (f) to TNC (m)		
54311/203	7 mm to N (f)		
54311/204	7 mm to TNC (m)		
54311/205	7 mm to TNC (f)		
54311/136	TNC (m) to TNC (m)		
54311/107	3.5 mm (f) to 3.5 mm (f)		
54311/165	3.5 mm (m) to 3.5 mm (f)		
54311/164	3.5 mm (m) to 3.5 mm (m)		
54311/162	2.92 mm (m) to 2.92 mm (m)		
54311/206	2.92 mm (m) to 2.92 mm (f)		
54311/207	2.92 mm (f) to 2.92 mm (f)		
			<b>Standard Adapters</b>
			N (f) to SMA (f)
			N (m) to SMA (f)
			TNC (m) to SMA (m)
			<b>Miscellaneous Electrical Cables</b>
			Positive Voltage Measurement Cable
			Negative Voltage Measurement Cable
			GPIO Cable
			BNC (m) to BNC (m) 1.5 m
			Parallel Printer Interface Cable
			Autotester Adapter Cable 0.5 m
			Autotester Adapter Cable 1.5 m
			<b>Standard Microwave Cables</b>
			0.5 m, 18 GHz, N (m) to N (m)
			0.5 m, 26.5 GHz, 3.5 mm (m) to 3.5 mm (m)
			0.5 m, 40 GHz, 2.92 mm (m) to 2.92 mm (m)
			<b>Attenuators</b>
			Precision Fixed Coaxial Attenuator 3 dB DC to 18 GHz 5 W, N(m) to N(f)
			Precision Fixed Coaxial Attenuator 6 dB DC to 18 GHz 5 W, N(m) to N(f)
			Precision Fixed Coaxial Attenuator 10 dB DC to 18 GHz 5 W, N(m) to N(f)
			Precision Fixed Coaxial Attenuator 20 dB DC to 18 GHz 5 W, N(m) to N(f)
			<b>Software Support</b>
			MIPlot Software Pack
			<b>MISCELLANEOUS</b>
			3.5 mm Torque Wrench
			Compact Keyboard
			1.25 GHz Active Probe
			Power supply for 2388









